

MODEL 6730

ELECTRONIC CONVERTER/CHARGER

With AC and DC Distribution



High reliability and value for smaller RV classes.

The Model 6730 electronic converter/charger from Parallax is the perfect power solution for smaller RV classes. The filtered DC power is free from spikes and surges, ensuring bright lighting and smooth operation of amenities. The DC output of 30 amps brings convenience and reliability to the user's RV experiences.

Rugged steel construction provides durability which withstands the rigors of RVing. Parallax provides even more value with extensive AC/DC distribution which is integrated into the unit. All AC circuit breakers are provided pre-wired. Included are one 30-amp main AC circuit breaker, one 20-amp circuit breaker, and two 15-amp circuit breakers. Locations for five DC fuses and a fuse for reverse polarity also are provided.

Specifications

Model 6730 Converter/Charger

Product Dimensions

Width: 13.75"
Height: 7"
Depth: 5.5"
(face plate 13.75" W x 7" H)

Cut-out Area Required

Width: 12.75"
Height: 6.25"

Weight

8.5 lbs. (does not include package)

DC Output

30 amps

AC Distribution

(1) 30 amp main circuit breaker
(1) 20 amp branch circuit breaker
(2) 15 amp branch circuit breakers
All circuit breakers are provided pre-wired

DC Distribution

(5) DC fuse circuit locations
(1) reverse polarity protection fuse location
Reverse polarity fuse included; load fuses not supplied.
Meets or exceeds listing requirements for use in an RV.



Sales Office
596 Broadway
Anderson, IN 46012
800-443-4859 Fax 765-608-5036
www.parallaxpower.com

Corporate Office
5508 128th Street E.
Puyallup, WA 98373

